

HOMEGUARD™

make your home safe and secure



Be assured that your house is safe when you leave: you will receive a warning by telephone if there are any problems.

Home alone, but not afraid: use the panic button to warn neighbours or friends in case of an emergency.

Frighten off burglars with the built-in siren.

MARMITEK®



base unit




remote control

HOMEGUARD

- Be assured that your house is safe when you leave: when anything happens you (or your neighbours) are warned by telephone. Three programmable telephone numbers.
- Home alone, but not afraid: use the panic function to warn your neighbours or friends in case of an emergency. Silent alarm.
- No extra parts required: motion detector, phone dialler and siren are built in.
- Small and compact.
- Configuration via keyboard and remote control (wireless, through walls and ceilings).
- Connectors for extra sensors, such as door/window contacts or temperature sensors.





HOW DOES IT WORK?



TELEPHONE



CONNECTION FOR
E.G. DOOR/WINDOW
CONTACT



230V



MAX. 4
REMOTE CONTROLS



SD90
WIRELESS
SMOKE DETECTOR
(OPTIONAL)



1. 90 dB siren.
2. PIR motion detector.
3. Built-in phone dialler.
4. Extra connection for e.g. temperature sensor or door/window contact.
5. Remote control to switch the alarm and panic function on or off.

TECHNICAL DATA

BASE UNIT

Range PIR: 180° - 6 m, 12 m in a straight line (PIR can be switched off).
 Alarm: 95dB (can be switched off).
 Power: 230VAC, 12VDC (adapter included).
 9V emergency battery (max. 8 hours when using alkaline battery).
 Phone dialler: R&TTE approved.
 max. 3 telephone numbers (max. 16 digits).
 Pause option for PABX/alarm system.
 Phone dialler stops after confirmation of receipt.
 Built-in voice chip with standard message (English, German, French, Dutch).
 External connection: Connection for external potential-free N/O or N/C contact (e.g. magnetic sensor).
 Dimensions: 130x75x60mm (HxWxD).
 Including: HomeGuard base station, remote control, power adapter, telephone cable, cable for external sensor, battery 9V for backup, user guide English, German, French, Dutch.

REMOTE CONTROL (KR21)

Frequency: 433.92MHz (works through floors and walls).
 Functions:
 1. Alarm on (with delay).
 2. Alarm off.
 3. Panic (direct alarm).
 Unique codes: 64000.
 Power: 3V lithium CR2016 (2x).
 Dimensions: 56x38x12mm.

Can be extended to max. 4 remote controls per base unit.
 The same remote control can be registered with several base units.

AVAILABLE

- HomeGuard set (HomeGuard base unit + KR21 remote control)
 Article number: 09155 09154 09156 09265 09263 09148
- Extra KR21 remote control
- Wireless smoke detector SD90

art. no. 09169
 art. no. 09652